

# Patient room solutions.



H2000VRI

EH2000 Cradle

## Healthcare Series Data Sheet

H2001-09, H2000, H2000VRI, EH2000, H2001-00

Phone: 1300 725 059  
Email: [sales@netip.com.au](mailto:sales@netip.com.au)  
Web Site: [www.netip.com.au](http://www.netip.com.au)

QUESTIONS: [sales@netip.com.au](mailto:sales@netip.com.au)  
SUPPORT: [support@netip.com.au](mailto:support@netip.com.au)

Scitec single-use disposable healthcare telephones and accessories help reduce patient room cross-contamination, cleaning and repair costs. Discover new telecom revenue sources, when you send the disposable patient room telephone home.

## HIGHLIGHTS

- Single-Line Telephones
- Compatible with All Major PBX Systems
- Single-Use Telephones Reduce Cross-Contamination and Increase Telecom Revenues (H2001-09/H2001-00/H2000VRI/H2000)
- Lighted On/Off Talk Key (H2001-09/H2001-00)
- Big Button Lighted Dial Pad (H2001-00/H2000VRI/H2000)
- Big Button Reflective Dial Pad (H2001-09)
- Visual Ring Indicator Light Provides Hard-of-Hearing Patients with a Visual Notification of an Incoming Call (H2001-09/H2001-00/H2000VRI)
- Bedrail Holder Helps Eliminate Bedside Clutter (EH2000)
- Side-Mounted RJ11 Data-port Provides Access for Laptops and Other Devices (H2000VRI/H2000)
- Industrial Grade Construction with Matte or Gloss Finish Design
- Non-Slip Base
- 3-Step Volume Control Key (H2001-09/H2001-00/H2000VRI/H2000)
- High/Low Ringer Volume Control
- HAC-Compatible Handset
- ADA-Compliant Volume Control
- Available in White
- 90 Day Warranty



# CONFIGURATIONS

## Single-Line One-Piece Telephone

H2001-00	Part Number 21105 (white)
H2001-09	Part Number 21195-09 (white)

## Single-Line Two-Piece Telephone

H2000	Part Number 20005 (white)
H2000VRI	Part Number 20015 (white)

## Bedrail Holder

EH2000	Part Number 211151 (white)
--------	----------------------------

# PRODUCT INFORMATION

### Installation Includes

- RJ11 Line Cords 15 ft/4.57 m
- Handset Coil Cord 10 ft/3.05 m
- Optional Wall Mount Bracket (not included)

### Line, MW, and Ringer Specification

- Line Voltage—Auto-Detect
- Line Current 20mA-80mA
- Auto-Detect for 90VDC Neon or Low Voltage LED Applications
- Ringer Equivalence—0.6B

### Unit Dimensions

- 8.25"(l) x 2.25"(w) x 1.5"(h) (H2001-09)
- 8.25"(l) x 2.5"(w) x 2.0"(h) (H2001-00)
- 9.0"(l) x 4.0"(w) x 4.0"(h) (H2000VRI/H2000)
- 9.0"(l) x 4.0"(w) x 4.0"(h) (EH2000)

### Packaging Weight

- Master Pack Quantities of 16 Units, 32lbs/14.51kg (H2001-09/  
H2001-00/H2000VRI/H2000/EH2000)

### Certifications

- FCC Part 68, FCC Part 15 & UL 1459 Ref.
- ADA/FCC Hearing Aid Compliant

### Flash Key (H2001-09/H2001-00)

### Telephone Bedrail Holder (EH2000)

- Fits Popular Healthcare Bed Models
- Convenient Side Mount Slide Lever Secures Holder to Rail



Phone: 1300 725 059  
Email: [sales@netip.com.au](mailto:sales@netip.com.au)  
Web Site: [www.netip.com.au](http://www.netip.com.au)

QUESTIONS: [sales@netip.com.au](mailto:sales@netip.com.au)  
SUPPORT: [support@netip.com.au](mailto:support@netip.com.au)

